

Job Site Charger Radio DMR300 / DMR301 12Vmax-18 V / AC





Capable of receiving











Battery charging function

- Able to charge LXT/CXT batteries when powered by AC with AC adaptor
- Clear sound quality can be enjoyed even during battery charging.

Charging time: min

| 12Vmax | | | 18V | | | | | |
|-------------------|--------------------|--------------------|--------------------|--------------------|--------------------|--------------------|--------------------|--------------------|
| BL1016 (1.5Ah) | BL1021B (2.0Ah) | BL1041B (4.0Ah) | BL1815N (1.5Ah) | BL1820B (2.0Ah) | BL1830B (3.0Ah) | BL1840B (4.0Ah) | BL1850B (5.0Ah) | BL1860B (6.0Ah) |
| 31 | 40 | 75 | 27 | 38 | 48 | 67 | 84 | 100 |



Charging status indication

- LCD screen indicates battery charging status; Charging, Charging completed, Standing-by for charging, harging error.
- It also indicates that the battery has reached 80% charge.



| Indicator for battery capacity | Charging status | | |
|-----------------------------------|--|--|--|
| (blinking) | Charging (less than 80%) | | |
| (blinking) | Charging (80% or more has been charged) | | |
| (lights up) | Charged (100%) | | |

Dust and shower-proof construction: IP64



For use in outdoor applications or harsh environments



AUX-IN jack



used as a stereo speaker by connecting to external audio source with a commercial connecting cable.

USB output port



Thakita

- allows for charging a mobile device.
- Type A USB socket for DC5V/ 2.4A USB output

Bottle opener

makita



Capable of receiving



(DMR301 only)

Dual power sources



The weight may differ depending on the attachment(s), including the battery cartridge. Items of standard equipment and specifications may vary by country or area.

Continuous run time (approx): hour

On a single full battery charge

| 12V max | BL1016 (1.5Ah) 6.3 | 18V | BL1815N(1.5Ah) 6.1 | BL1840B(4.0Ah) 16 |
|------------|----------------------------|-----|----------------------------|----------------------------|
| | BL1021B(2.0Ah) 8.2 | | BL1820B(2.0Ah) 8.2 | BL1850B(5.0Ah) 20.5 |
| | BL1041B(4.0Ah) 16.4 | | BL1830B(3.0Ah) 11.3 | BL1860B(6.0Ah) 24.7 |

Job Site Charger Radio

Standard Equipment :AC Adaptor, AA Battery

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan