



Flashlight Radio DMR050

Satisfy Professional's Needs

Cordless job site radio with LED flashlight



18V
LITHIUM-ION

14.4V
LITHIUM-ION

LXT
LITHIUM-ION



Large size front speaker produces high quality sound.
Speaker positioned in front for clear sound transmission to users



6 Position Pivoting Light Head
with positive stops at -60°, -30°, 0°, +30°, +60°, +90°



LCD digital display

3 x 1.4W LED for wide and bright illumination

**Illuminance:
1,600lx or more**



Powered by
14.4/ 18V (1.3Ah, 3.0Ah)
Li-ion Battery (option)

- Preset
- AM/FM digital tuning
- Volume level

Battery

Higher capacity
BL1830 18V-3.0Ah



Lightweight
BL1815 18V-1.3Ah



Higher capacity
BL1430 14.4V-3.0Ah



Lightweight
BL1415 14.4V-1.3Ah



Charger

DC18RA / DC18RC

Charging time
BL1815, BL1415: 15minutes
BL1830, BL1430: 22minutes



DC18SD

Charging time
BL1815, BL1415: 30minutes
BL1830, BL1430: 60minutes



Flashlight Radio

DMR050

Continuous use (hours)	6 - with BL1830, BL1430 / 2.5 - with BL1815, BL1415
Practical max output	2.0W-3.0Ah / 1.5W-1.3Ah
Frequency band	AM / FM : 522-1629kHz / 87.5-108 MHz
Dimensions (L x W x H)	263x75x196mm (10-3/8"x2-15/16"x7-3/4") with BL1830, BL1430 263x75x179mm (10-3/8"x2-15/16"x7") with BL1815, BL1415
Net Weight*	1.23kg (2.7lbs) with BL1830, 1.01kg (2.2lbs) with BL1815 1.14kg (2.5lbs) with BL1430, 0.95kg (2.1lbs) with BL1415

Standard Equipment :

Strap (Battery and Charger are sold separately.)

*Weight according to EPTA-Procedure 01/2003

Items of standard equipment and specifications may vary by country or area.

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN BB-BB