




# Li-ion In-Line Cordless Screwdriver DF001DW (with 81 pcs bit assortment and Charger)



LED job light



Lamp switch

ON / OFF switch with reverse / forward control



USB connector with rubber cover



Micro USB

straight style

Can be used as both of straight style and pistol style

pistol style



Can be used as a hand Screwdriver

**Comes with 81 pcs assortment and Charger**



**Drive type**

Phillips (PH)	PZ	Hex (H)
T	Slotted (SL)	

- C-form 25mm Screw bit**  
 PZ : 0, 1, 2, 3 (3pc each)  
 Hex : 2, 2.5, 3, 4, 5, 6 (2pc each)  
 T : 10, 15, 20, 25, 27, 30, 40 (3pc each)  
 SL : 0.5x3, 0.5x4, 0.6x4.5, 0.8x5.5, 1.0x5.5, 1.2x6.5 (2pc each)  
 PH : 0, 1, 2 (3pc each), 3 (2pc each)

**Charger (ADP07)**  
 Charging time: 3 to 5 hours (DC5V/ 1A USB output)

- E-form 50mm Screw bit**  
 T : 20, 25, 30 (1pc each)  
 PH : 1, 2, 3 (1pc each)

- E-form Socket Wrench**  
 5, 6, 7, 8, 9, 10mm (1pc each)

- E-form magnetic bit holder**  
 60mm (1pc each)



Convenient in a narrow space

## In-Line Cordless Screwdriver DF001D

Reversing	<b>Fastening Capacities</b> Wood Screw: ø3.8 x 32 mm (1/8" x 1-1/4")
Built-in Job Light	<b>No Load Speed (RPM)</b> 220
Carrying Case	<b>Max Fastening Torque</b> Hard / Soft: 4.0 / 3.0 N·m (35 / 27 in.lbs.)
	<b>Max lock torque</b> 6.0 N·m (53 in.lbs.)
	<b>Vibration Level</b> Screwdriving without Impact: 2.5 m/s <sup>2</sup> or less
	<b>Sound Pressure Level</b> 70 dB(A) or less
	<b>Charging Time (hours)</b> 3 - 5
	<b>Dimensions (L x W x H)</b> Straight style: 287x47x51mm (11-1/4"x1-7/8"x2")
	Pistol style: 205x47x51mm (8-1/8"x1-7/8"x2")
	<b>Net weight</b> 0.36 kg (0.8 lbs.)

**Standard Equipment :** DF001DW: Bit set (81 pcs), Charger, USB Cable

weight according to EPTA-Procedure 01/ver.2.1  
 Items of standard equipment and specifications may vary by country or area.

**Makita Corporation**

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN 201701